



Clifton Cameras Product Specification

Boya BY-PVM1000L Professional Shotgun Mic Full Spec

Polar pattern: Super-Cardioid

Output Impedance: 280 Ω or more(phantom) 380 Ω or more(battery)

Frequency Response: 25-20000Hz

Sensitivity: -33dB +/- 1dB / 0dB=1V/Pa, 1kHz

S/N Ratio: 80dB or More (1KHz at 1Pa)

Power Source: 1.5v battery or 48v phantom

Plug: mini-pin plug (3-pin XLR)